

# **The mac80211 subsystem for kernel developers**

**Johannes Berg**

**`johannes@sipsolutions.net`**

# **The mac80211 subsystem for kernel developers**

by Johannes Berg

Copyright © 2007, 2008 Johannes Berg

mac80211 is the Linux stack for 802.11 hardware that implements only partial functionality in hard- or firmware. This document defines the interface between mac80211 and low-level hardware drivers.

If you're reading this document and not the header file itself, it will be incomplete because not all documentation has been converted yet.

This documentation is free software; you can redistribute it and/or modify it under the terms of the GNU General Public License version 2 as published by the Free Software Foundation.

This documentation is distributed in the hope that it will be useful, but WITHOUT ANY WARRANTY; without even the implied warranty of MERCHANTABILITY or FITNESS FOR A PARTICULAR PURPOSE. See the GNU General Public License for more details.

You should have received a copy of the GNU General Public License along with this documentation; if not, write to the Free Software Foundation, Inc., 59 Temple Place, Suite 330, Boston, MA 02111-1307 USA

For more details see the file COPYING in the source distribution of Linux.

# Table of Contents

<b>I. The basic mac80211 driver interface.....</b>	<b>vii</b>
1. Basic hardware handling.....	1
struct ieee80211_hw .....	1
enum ieee80211_hw_flags.....	3
SET_IEEE80211_DEV.....	5
SET_IEEE80211_PERM_ADDR.....	6
struct ieee80211_ops.....	7
ieee80211_alloc_hw .....	11
ieee80211_register_hw .....	12
ieee80211_get_tx_led_name.....	13
ieee80211_get_rx_led_name .....	14
ieee80211_get_assoc_led_name .....	15
ieee80211_get_radio_led_name .....	16
ieee80211_unregister_hw .....	16
ieee80211_free_hw .....	17
2. PHY configuration .....	19
struct ieee80211_conf .....	19
enum ieee80211_conf_flags.....	20
3. Virtual interfaces.....	23
enum ieee80211_if_types .....	23
struct ieee80211_if_init_conf .....	24
struct ieee80211_if_conf.....	25
4. Receive and transmit processing.....	29
4.1. what should be here .....	29
4.2. Frame format.....	29
4.3. Alignment issues.....	29
4.4. Calling into mac80211 from interrupts.....	29
4.5. functions/definitions.....	30
struct ieee80211_rx_status.....	30
enum mac80211_rx_flags .....	31
/usr/src/packages/BUILD/linux-2.6.27.19-	
5//include/net/mac80211.h	
33	
/usr/src/packages/BUILD/linux-2.6.27.19-	
5//include/net/mac80211.h	
34	
ieee80211_rx.....	34
ieee80211_rx_irqsafe .....	35
ieee80211_tx_status .....	36
ieee80211_tx_status_irqsafe .....	37
ieee80211_rts_get .....	38

ieee80211_rts_duration.....	40
ieee80211_ctstoself_get.....	41
ieee80211_ctstoself_duration .....	42
ieee80211_generic_frame_duration.....	43
ieee80211_get_hdrlen_from_skb.....	44
ieee80211_get_hdrlen .....	45
ieee80211_wake_queue .....	46
ieee80211_stop_queue.....	47
/usr/src/packages/BUILD/linux-2.6.27.19-5//include/net/mac80211.h	
48	
ieee80211_stop_queues .....	49
ieee80211_wake_queues.....	49
5. Frame filtering.....	51
enum ieee80211_filter_flags .....	51
<b>II. Advanced driver interface.....</b>	<b>55</b>
6. Hardware crypto acceleration .....	57
enum set_key_cmd.....	57
struct ieee80211_key_conf .....	58
enum ieee80211_key_alg.....	60
enum ieee80211_key_flags .....	61
7. Multiple queues and QoS support.....	63
struct ieee80211_tx_queue_params .....	63
/usr/src/packages/BUILD/linux-2.6.27.19-5//include/net/mac80211.h...	64
/usr/src/packages/BUILD/linux-2.6.27.19-5//include/net/mac80211.h...	64
8. Access point mode support .....	67
ieee80211_get_buffered_bc .....	67
ieee80211_beacon_get.....	68
9. Supporting multiple virtual interfaces .....	71
10. Hardware scan offload .....	73
ieee80211_scan_completed .....	73
<b>III. Rate control interface.....</b>	<b>75</b>
11. dummy chapter.....	77
<b>IV. Internals.....</b>	<b>79</b>
12. Key handling .....	81
12.1. Key handling basics .....	81
12.2. MORE TBD .....	81
13. Receive processing.....	83
14. Transmit processing .....	85
15. Station info handling.....	87
15.1. Programming information.....	87
struct sta_info.....	87

enum ieee80211_sta_info_flags.....	93
15.2. STA information lifetime rules .....	95
16. Synchronisation.....	97



# I. The basic mac80211 driver interface

## Table of Contents

<b>1. Basic hardware handling.....</b>	<b>1</b>
<b>2. PHY configuration .....</b>	<b>19</b>
<b>3. Virtual interfaces.....</b>	<b>23</b>
<b>4. Receive and transmit processing .....</b>	<b>29</b>
<b>5. Frame filtering.....</b>	<b>51</b>

You should read and understand the information contained within this part of the book while implementing a driver. In some chapters, advanced usage is noted, that may be skipped at first.

This part of the book only covers station and monitor mode functionality, additional information required to implement the other modes is covered in the second part of the book.





# Chapter 1. Basic hardware handling

TBD

This chapter shall contain information on getting a hw struct allocated and registered with mac80211.

Since it is required to allocate rates/modes before registering a hw struct, this chapter shall also contain information on setting up the rate/mode structs.

Additionally, some discussion about the callbacks and the general programming model should be in here, including the definition of ieee80211\_ops which will be referred to a lot.

Finally, a discussion of hardware capabilities should be done with references to other parts of the book.

## struct ieee80211\_hw

### LINUX

Kernel Hackers Manual February 2009

### Name

struct ieee80211\_hw — hardware information and state

### Synopsis

```
struct ieee80211_hw {
    struct ieee80211_conf conf;
    struct wiphy * wiphy;
    struct workqueue_struct * workqueue;
    const char * rate_control_algorithm;
    void * priv;
    u32 flags;
    unsigned int extra_tx_headroom;
    int channel_change_time;
    int vif_data_size;
    u16 queues;
    u16 ampdu_queues;
    u16 max_listen_interval;
    s8 max_signal;
};
```

## Members

`conf`

struct `ieee80211_conf`, device configuration, don't use.

`wiphy`

This points to the struct `wiphy` allocated for this 802.11 PHY. You must fill in the `perm_addr` and `dev` members of this structure using `SET_IEEE80211_DEV` and `SET_IEEE80211_PERM_ADDR`. Additionally, all supported bands (with channels, bitrates) are registered here.

`workqueue`

single threaded workqueue available for driver use, allocated by `mac80211` on registration and flushed when an interface is removed.

`rate_control_algorithm`

rate control algorithm for this hardware. If unset (NULL), the default algorithm will be used. Must be set before calling `ieee80211_register_hw`.

`priv`

pointer to private area that was allocated for driver use along with this structure.

`flags`

hardware flags, see enum `ieee80211_hw_flags`.

`extra_tx_headroom`

headroom to reserve in each transmit skb for use by the driver (e.g. for transmit headers.)

`channel_change_time`

time (in microseconds) it takes to change channels.

`vif_data_size`

size (in bytes) of the `drv_priv` data area within struct `ieee80211_vif`.

`queues`

number of available hardware transmit queues for data packets. WMM/QoS requires at least four, these queues need to have configurable access parameters.

`ampdu_queues`

number of available hardware transmit queues for A-MPDU packets, these have no access parameters because they're used only for A-MPDU frames. Note that `mac80211` will not currently use any of the regular queues for aggregation.

`max_listen_interval`

max listen interval in units of beacon interval that HW supports

`max_signal`

Maximum value for signal (rssi) in RX information, used only when `IEEE80211_HW_SIGNAL_UNSPEC` or `IEEE80211_HW_SIGNAL_DB`

## Description

This structure contains the configuration and hardware information for an 802.11 PHY.

## NOTICE

All work performed on this workqueue should NEVER acquire the RTNL lock (i.e. Don't use the function `ieee80211_iterate_active_interfaces`)

## enum ieee80211\_hw\_flags

### LINUX

Kernel Hackers Manual February 2009

### Name

`enum ieee80211_hw_flags` — hardware flags

## Synopsis

```
enum ieee80211_hw_flags {
    IEEE80211_HW_RX_INCLUDES_FCS,
    IEEE80211_HW_HOST_BROADCAST_PS_BUFFERING,
    IEEE80211_HW_2GHZ_SHORT_SLOT_INCAPABLE,
    IEEE80211_HW_2GHZ_SHORT_PREAMBLE_INCAPABLE,
    IEEE80211_HW_SIGNAL_UNSPEC,
    IEEE80211_HW_SIGNAL_DB,
    IEEE80211_HW_SIGNAL_DBM,
    IEEE80211_HW_NOISE_DBM,
    IEEE80211_HW_SPECTRUM_MGMT
};
```

## Constants

### IEEE80211\_HW\_RX\_INCLUDES\_FCS

Indicates that received frames passed to the stack include the FCS at the end.

### IEEE80211\_HW\_HOST\_BROADCAST\_PS\_BUFFERING

Some wireless LAN chipsets buffer broadcast/multicast frames for power saving stations in the hardware/firmware and others rely on the host system for such buffering. This option is used to configure the IEEE 802.11 upper layer to buffer broadcast and multicast frames when there are power saving stations so that the driver can fetch them with `ieee80211_get_buffered_bc`.

### IEEE80211\_HW\_2GHZ\_SHORT\_SLOT\_INCAPABLE

Hardware is not capable of short slot operation on the 2.4 GHz band.

### IEEE80211\_HW\_2GHZ\_SHORT\_PREAMBLE\_INCAPABLE

Hardware is not capable of receiving frames with short preamble on the 2.4 GHz band.

### IEEE80211\_HW\_SIGNAL\_UNSPEC

Hardware can provide signal values but we don't know its units. We expect values between 0 and `max_signal`. If possible please provide dB or dBm instead.

### IEEE80211\_HW\_SIGNAL\_DB

Hardware gives signal values in dB, decibel difference from an arbitrary, fixed reference. We expect values between 0 and `max_signal`. If possible please

provide dBm instead.

#### IEEE80211\_HW\_SIGNAL\_DBM

Hardware gives signal values in dBm, decibel difference from one milliwatt. This is the preferred method since it is standardized between different devices. *max\_signal* does not need to be set.

#### IEEE80211\_HW\_NOISE\_DBM

Hardware can provide noise (radio interference) values in units dBm, decibel difference from one milliwatt.

#### IEEE80211\_HW\_SPECTRUM\_MGMT

Hardware supports spectrum management defined in 802.11h Measurement, Channel Switch, Quieting, TPC

## Description

These flags are used to indicate hardware capabilities to the stack. Generally, flags here should have their meaning done in a way that the simplest hardware doesn't need setting any particular flags. There are some exceptions to this rule, however, so you are advised to review these flags carefully.

## SET\_IEEE80211\_DEV

### LINUX

Kernel Hackers Manual February 2009

### Name

SET\_IEEE80211\_DEV — set device for 802.11 hardware

## Synopsis

```
void SET_IEEE80211_DEV (struct ieee80211_hw * hw, struct
device * dev);
```

## Arguments

*hw*

the struct ieee80211\_hw to set the device for

*dev*

the struct device of this 802.11 device

# SET\_IEEE80211\_PERM\_ADDR

## LINUX

Kernel Hackers Manual February 2009

## Name

SET\_IEEE80211\_PERM\_ADDR — set the permanenet MAC address for 802.11 hardware

## Synopsis

```
void SET_IEEE80211_PERM_ADDR (struct ieee80211_hw * hw, u8 *
addr);
```

## Arguments

*hw*

the struct `ieee80211_hw` to set the MAC address for

*addr*

the address to set

## struct `ieee80211_ops`

### LINUX

Kernel Hackers Manual February 2009

### Name

struct `ieee80211_ops` — callbacks from `mac80211` to the driver

### Synopsis

```
struct ieee80211_ops {
    int (* tx) (struct ieee80211_hw *hw, struct sk_buff *skb);
    int (* start) (struct ieee80211_hw *hw);
    void (* stop) (struct ieee80211_hw *hw);
    int (* add_interface) (struct ieee80211_hw *hw, struct ieee80211_if_init);
    void (* remove_interface) (struct ieee80211_hw *hw, struct ieee80211_if_);
    int (* config) (struct ieee80211_hw *hw, struct ieee80211_conf *conf);
    int (* config_interface) (struct ieee80211_hw *hw, struct ieee80211_vif );
    void (* bss_info_changed) (struct ieee80211_hw *hw, struct ieee80211_vif );
    void (* configure_filter) (struct ieee80211_hw *hw, unsigned int changed);
    int (* set_tim) (struct ieee80211_hw *hw, int aid, int set);
    int (* set_key) (struct ieee80211_hw *hw, enum set_key_cmd cmd, const u8 );
    void (* update_tkip_key) (struct ieee80211_hw *hw, struct ieee80211_key );
    int (* hw_scan) (struct ieee80211_hw *hw, u8 *ssid, size_t len);
    int (* get_stats) (struct ieee80211_hw *hw, struct ieee80211_low_level_st );
    void (* get_tkip_seq) (struct ieee80211_hw *hw, u8 hw_key_idx, u32 *iv32 );
    int (* set_rts_threshold) (struct ieee80211_hw *hw, u32 value);
    int (* set_frag_threshold) (struct ieee80211_hw *hw, u32 value);
    int (* set_retry_limit) (struct ieee80211_hw *hw, u32 short_retry, u32 lo
```

```
void (* sta_notify) (struct ieee80211_hw *hw, struct ieee80211_vif *vif,  
int (* conf_tx) (struct ieee80211_hw *hw, u16 queue, const struct ieee80211_tx_control *tx_ctrl),  
int (* get_tx_stats) (struct ieee80211_hw *hw, struct ieee80211_tx_queue *tx_queue),  
u64 (* get_tsf) (struct ieee80211_hw *hw);  
void (* reset_tsf) (struct ieee80211_hw *hw);  
int (* tx_last_beacon) (struct ieee80211_hw *hw);  
int (* ampdu_action) (struct ieee80211_hw *hw, enum ieee80211_ampdu_mlme_action action,  
};
```

## Members

### tx

Handler that 802.11 module calls for each transmitted frame. `skb` contains the buffer starting from the IEEE 802.11 header. The low-level driver should send the frame out based on configuration in the TX control data. This handler should, preferably, never fail and stop queues appropriately, more importantly, however, it must never fail for A-MPDU-queues. Must be implemented and atomic.

### start

Called before the first netdevice attached to the hardware is enabled. This should turn on the hardware and must turn on frame reception (for possibly enabled monitor interfaces.) Returns negative error codes, these may be seen in userspace, or zero. When the device is started it should not have a MAC address to avoid acknowledging frames before a non-monitor device is added. Must be implemented.

### stop

Called after last netdevice attached to the hardware is disabled. This should turn off the hardware (at least it must turn off frame reception.) May be called right after `add_interface` if that rejects an interface. Must be implemented.

### add\_interface

Called when a netdevice attached to the hardware is enabled. Because it is not called for monitor mode devices, *open* and *stop* must be implemented. The driver should perform any initialization it needs before the device can be enabled. The initial configuration for the interface is given in the `conf` parameter. The callback may refuse to add an interface by returning a negative error code (which will be seen in userspace.) Must be implemented.



`remove_interface`

Notifies a driver that an interface is going down. The *stop* callback is called after this if it is the last interface and no monitor interfaces are present. When all interfaces are removed, the MAC address in the hardware must be cleared so the device no longer acknowledges packets, the *mac\_addr* member of the *conf* structure is, however, set to the MAC address of the device going away. Hence, this callback must be implemented.

`config`

Handler for configuration requests. IEEE 802.11 code calls this function to change hardware configuration, e.g., channel.

`config_interface`

Handler for configuration requests related to interfaces (e.g. BSSID changes.)

`bss_info_changed`

Handler for configuration requests related to BSS parameters that may vary during BSS's lifespan, and may affect low level driver (e.g. assoc/disassoc status, erp parameters). This function should not be used if no BSS has been set, unless for association indication. The *changed* parameter indicates which of the bss parameters has changed when a call is made.

`configure_filter`

Configure the device's RX filter. See the section "Frame filtering" for more information. This callback must be implemented and atomic.

`set_tim`

Set TIM bit. *mac80211* calls this function when a TIM bit must be set or cleared for a given AID. Must be atomic.

`set_key`

See the section "Hardware crypto acceleration" This callback can sleep, and is only called between *add\_interface* and *remove\_interface* calls, i.e. while the interface with the given *local\_address* is enabled.

`update_tkip_key`

See the section "Hardware crypto acceleration" This callback will be called in the context of Rx. Called for drivers which set *IEEE80211\_KEY\_FLAG\_TKIP\_REQ\_RX\_P1\_KEY*.

`hw_scan`

Ask the hardware to service the scan request, no need to start the scan state machine in stack. The scan must honour the channel configuration done by the regulatory agent in the wiphy's registered bands.

`get_stats`

return low-level statistics

`get_tkip_seq`

If your device implements TKIP encryption in hardware this callback should be provided to read the TKIP transmit IVs (both IV32 and IV16) for the given key from hardware.

`set_rts_threshold`

Configuration of RTS threshold (if device needs it)

`set_frag_threshold`

Configuration of fragmentation threshold. Assign this if the device does fragmentation by itself; if this method is assigned then the stack will not do fragmentation.

`set_retry_limit`

Configuration of retry limits (if device needs it)

`sta_notify`

Notifies low level driver about addition or removal of associated station or AP.

`conf_tx`

Configure TX queue parameters (EDCF (aifs, cw\_min, cw\_max), bursting) for a hardware TX queue. Must be atomic.

`get_tx_stats`

Get statistics of the current TX queue status. This is used to get number of currently queued packets (queue length), maximum queue size (limit), and total number of packets sent using each TX queue (count). The 'stats' pointer points to an array that has `hw->queues + hw->ampdu_queues` items.

`get_tsf`

Get the current TSF timer value from firmware/hardware. Currently, this is only used for IBSS mode debugging and, as such, is not a required function. Must be atomic.

`reset_tsf`

Reset the TSF timer and allow firmware/hardware to synchronize with other STAs in the IBSS. This is only used in IBSS mode. This function is optional if the firmware/hardware takes full care of TSF synchronization.

`tx_last_beacon`

Determine whether the last IBSS beacon was sent by us. This is needed only for IBSS mode and the result of this function is used to determine whether to reply to Probe Requests.

`ampdu_action`

Perform a certain A-MPDU action The RA/TID combination determines the destination and TID we want the ampdu action to be performed for. The action is defined through `ieee80211_ampdu_mlme_action`. Starting sequence number (*ssn*) is the first frame we expect to perform the action on. notice that TX/RX\_STOP can pass NULL for this parameter.

## Description

This structure contains various callbacks that the driver may handle or, in some cases, must handle, for example to configure the hardware to a new channel or to transmit a frame.

# ieee80211\_alloc\_hw

## LINUX

Kernel Hackers Manual February 2009

## Name

`ieee80211_alloc_hw` — Allocate a new hardware device

## Synopsis

```
struct ieee80211_hw * ieee80211_alloc_hw (size_t  
priv_data_len, const struct ieee80211_ops * ops);
```

## Arguments

*priv\_data\_len*

length of private data

*ops*

callbacks for this device

## Description

This must be called once for each hardware device. The returned pointer must be used to refer to this device when calling other functions. `mac80211` allocates a private data area for the driver pointed to by *priv* in struct `ieee80211_hw`, the size of this area is given as *priv\_data\_len*.

# ieee80211\_register\_hw

## LINUX

Kernel Hackers Manual February 2009

## Name

`ieee80211_register_hw` — Register hardware device

## Synopsis

```
int ieee80211_register_hw (struct ieee80211_hw * hw);
```

## Arguments

*hw*

the device to register as returned by `ieee80211_alloc_hw`

## Description

You must call this function before any other functions in `mac80211`. Note that before a hardware can be registered, you need to fill the contained wiphy's information.

## ieee80211\_get\_tx\_led\_name

### LINUX

Kernel Hackers Manual February 2009

## Name

`ieee80211_get_tx_led_name` — get name of TX LED

## Synopsis

```
char * ieee80211_get_tx_led_name (struct ieee80211_hw * hw);
```

## Arguments

*hw*

the hardware to get the LED trigger name for

## Description

mac80211 creates a transmit LED trigger for each wireless hardware that can be used to drive LEDs if your driver registers a LED device. This function returns the name (or `NULL` if not configured for LEDs) of the trigger so you can automatically link the LED device.

# ieee80211\_get\_rx\_led\_name

## LINUX

Kernel Hackers Manual February 2009

## Name

`ieee80211_get_rx_led_name` — get name of RX LED

## Synopsis

```
char * ieee80211_get_rx_led_name (struct ieee80211_hw * hw);
```

## Arguments

*hw*

the hardware to get the LED trigger name for

## Description

mac80211 creates a receive LED trigger for each wireless hardware that can be used to drive LEDs if your driver registers a LED device. This function returns the name (or `NULL` if not configured for LEDs) of the trigger so you can automatically link the LED device.

# ieee80211\_get\_assoc\_led\_name

## LINUX

Kernel Hackers Manual February 2009

## Name

`ieee80211_get_assoc_led_name` — get name of association LED

## Synopsis

```
char * ieee80211_get_assoc_led_name (struct ieee80211_hw *  
hw);
```

## Arguments

*hw*

the hardware to get the LED trigger name for

## Description

mac80211 creates a association LED trigger for each wireless hardware that can be used to drive LEDs if your driver registers a LED device. This function returns the

name (or `NULL` if not configured for LEDs) of the trigger so you can automatically link the LED device.

## ieee80211\_get\_radio\_led\_name

### LINUX

Kernel Hackers Manual February 2009

### Name

`ieee80211_get_radio_led_name` — get name of radio LED

### Synopsis

```
char * ieee80211_get_radio_led_name (struct ieee80211_hw *  
hw);
```

### Arguments

*hw*

the hardware to get the LED trigger name for

### Description

mac80211 creates a radio change LED trigger for each wireless hardware that can be used to drive LEDs if your driver registers a LED device. This function returns the name (or `NULL` if not configured for LEDs) of the trigger so you can automatically link the LED device.



# ieee80211\_unregister\_hw

## LINUX

Kernel Hackers Manual February 2009

### Name

ieee80211\_unregister\_hw — Unregister a hardware device

### Synopsis

```
void ieee80211_unregister_hw (struct ieee80211_hw * hw);
```

### Arguments

*hw*

the hardware to unregister

### Description

This function instructs mac80211 to free allocated resources and unregister netdevices from the networking subsystem.

# ieee80211\_free\_hw

## LINUX

## Name

`ieee80211_free_hw` — free hardware descriptor

## Synopsis

```
void ieee80211_free_hw (struct ieee80211_hw * hw);
```

## Arguments

*hw*

the hardware to free

## Description

This function frees everything that was allocated, including the private data for the driver. You must call `ieee80211_unregister_hw` before calling this function.

# Chapter 2. PHY configuration

TBD

This chapter should describe PHY handling including start/stop callbacks and the various structures used.

## struct ieee80211\_conf

**LINUX**

Kernel Hackers Manual February 2009

### Name

struct ieee80211\_conf — configuration of the device

### Synopsis

```
struct ieee80211_conf {
    int radio_enabled;
    int beacon_int;
    u16 listen_interval;
    u32 flags;
    int power_level;
    int max_antenna_gain;
    u8 antenna_sel_tx;
    u8 antenna_sel_rx;
    struct ieee80211_channel * channel;
    struct ieee80211_ht_info ht_conf;
    struct ieee80211_ht_bss_info ht_bss_conf;
};
```

### Members

radio\_enabled

when zero, driver is required to switch off the radio. TODO make a flag

## Chapter 2. PHY configuration

`beacon_int`

beacon interval (TODO make interface config)

`listen_interval`

listen interval in units of beacon interval

`flags`

configuration flags defined above

`power_level`

requested transmit power (in dBm)

`max_antenna_gain`

maximum antenna gain (in dBi)

`antenna_sel_tx`

transmit antenna selection, 0: default/diversity, 1/2: antenna 0/1

`antenna_sel_rx`

receive antenna selection, like *antenna\_sel\_tx*

`channel`

the channel to tune to

`ht_conf`

describes current self configuration of 802.11n HT capabilities

`ht_bss_conf`

describes current BSS configuration of 802.11n HT parameters

## Description

This struct indicates how the driver shall configure the hardware.

# enum ieee80211\_conf\_flags

## LINUX

Kernel Hackers Manual February 2009

## Name

enum ieee80211\_conf\_flags — configuration flags

## Synopsis

```
enum ieee80211_conf_flags {
    IEEE80211_CONF_SHORT_SLOT_TIME,
    IEEE80211_CONF_RADIOTAP,
    IEEE80211_CONF_SUPPORT_HT_MODE,
    IEEE80211_CONF_PS
};
```

## Constants

IEEE80211\_CONF\_SHORT\_SLOT\_TIME

use 802.11g short slot time

IEEE80211\_CONF\_RADIOTAP

add radiotap header at receive time (if supported)

IEEE80211\_CONF\_SUPPORT\_HT\_MODE

use 802.11n HT capabilities (if supported)

IEEE80211\_CONF\_PS

Enable 802.11 power save mode

## Description

Flags to define PHY configuration options



# Chapter 3. Virtual interfaces

TBD

This chapter should describe virtual interface basics that are relevant to the driver (VLANs, MGMT etc are not.) It should explain the use of the `add_iface/remove_iface` callbacks as well as the interface configuration callbacks.

Things related to AP mode should be discussed there.

Things related to supporting multiple interfaces should be in the appropriate chapter, a BIG FAT note should be here about this though and the recommendation to allow only a single interface in STA mode at first!

## enum ieee80211\_if\_types

**LINUX**

Kernel Hackers Manual February 2009

### Name

`enum ieee80211_if_types` — types of 802.11 network interfaces

### Synopsis

```
enum ieee80211_if_types {
    IEEE80211_IF_TYPE_INVALID,
    IEEE80211_IF_TYPE_AP,
    IEEE80211_IF_TYPE_STA,
    IEEE80211_IF_TYPE_IBSS,
    IEEE80211_IF_TYPE_MESH_POINT,
    IEEE80211_IF_TYPE_MNTR,
    IEEE80211_IF_TYPE_WDS,
    IEEE80211_IF_TYPE_VLAN
};
```

## Constants

IEEE80211\_IF\_TYPE\_INVALID

invalid interface type, not used by mac80211 itself

IEEE80211\_IF\_TYPE\_AP

interface in AP mode.

IEEE80211\_IF\_TYPE\_STA

interface in STA (client) mode.

IEEE80211\_IF\_TYPE\_IBSS

interface in IBSS (ad-hoc) mode.

IEEE80211\_IF\_TYPE\_MESH\_POINT

802.11s mesh point

IEEE80211\_IF\_TYPE\_MNTR

interface in monitor (rfmon) mode.

IEEE80211\_IF\_TYPE\_WDS

interface in WDS mode.

IEEE80211\_IF\_TYPE\_VLAN

VLAN interface bound to an AP, drivers will never see this type.

## struct ieee80211\_if\_init\_conf

### LINUX

Kernel Hackers Manual February 2009

### Name

struct ieee80211\_if\_init\_conf — initial configuration of an interface



## Synopsis

```
struct ieee80211_if_init_conf {  
    enum ieee80211_if_types type;  
    struct ieee80211_vif * vif;  
    void * mac_addr;  
};
```

## Members

`type`

one of enum `ieee80211_if_types` constants. Determines the type of added/removed interface.

`vif`

pointer to a driver-use per-interface structure. The pointer itself is also used for various functions including `ieee80211_beacon_get` and `ieee80211_get_buffered_bc`.

`mac_addr`

pointer to MAC address of the interface. This pointer is valid until the interface is removed (i.e. it cannot be used after `remove_interface` callback was called for this interface).

## Description

This structure is used in `add_interface` and `remove_interface` callbacks of `struct ieee80211_hw`.

When you allow multiple interfaces to be added to your PHY, take care that the hardware can actually handle multiple MAC addresses. However, also take care that when there's no interface left with `mac_addr != NULL` you remove the MAC address from the device to avoid acknowledging packets in pure monitor mode.

# struct ieee80211\_if\_conf

## LINUX

Kernel Hackers Manual February 2009

### Name

struct ieee80211\_if\_conf — configuration of an interface

### Synopsis

```
struct ieee80211_if_conf {  
    u32 changed;  
    u8 * bssid;  
    u8 * ssid;  
    size_t ssid_len;  
};
```

### Members

changed

parameters that have changed, see enum ieee80211\_if\_conf\_change.

bssid

BSSID of the network we are associated to/creating.

ssid

used (together with *ssid\_len*) by drivers for hardware that generate beacons independently. The pointer is valid only during the `config_interface` call, so copy the value somewhere if you need it.

ssid\_len

length of the *ssid* field.

## **Description**

This structure is passed to the `config_interface` callback of struct `ieee80211_hw`.



# Chapter 4. Receive and transmit processing

## 4.1. what should be here

TBD

This should describe the receive and transmit paths in mac80211/the drivers as well as transmit status handling.

## 4.2. Frame format

As a general rule, when frames are passed between mac80211 and the driver, they start with the IEEE 802.11 header and include the same octets that are sent over the air except for the FCS which should be calculated by the hardware.

There are, however, various exceptions to this rule for advanced features:

The first exception is for hardware encryption and decryption offload where the IV/ICV may or may not be generated in hardware.

Secondly, when the hardware handles fragmentation, the frame handed to the driver from mac80211 is the MSDU, not the MPDU.

Finally, for received frames, the driver is able to indicate that it has filled a radiotap header and put that in front of the frame; if it does not do so then mac80211 may add this under certain circumstances.

## 4.3. Alignment issues

TBD

## 4.4. Calling into mac80211 from interrupts

Only `ieee80211_tx_status_irqsafe` and `ieee80211_rx_irqsafe` can be called in hardware interrupt context. The low-level driver must not call any other functions in hardware interrupt context. If there is a need for such call, the low-level

driver should first ACK the interrupt and perform the IEEE 802.11 code call after this, e.g. from a scheduled workqueue or even tasklet function.

NOTE: If the driver opts to use the `_irqsafe` functions, it may not also use the non-IRQ-safe functions!

## 4.5. functions/definitions

### struct ieee80211\_rx\_status

#### LINUX

Kernel Hackers Manual February 2009

#### Name

`struct ieee80211_rx_status` — receive status

#### Synopsis

```
struct ieee80211_rx_status {
    u64 mactime;
    enum ieee80211_band band;
    int freq;
    int signal;
    int noise;
    int qual;
    int antenna;
    int rate_idx;
    int flag;
};
```

#### Members

`mactime`

value in microseconds of the 64-bit Time Synchronization Function (TSF) timer when the first data symbol (MPDU) arrived at the hardware.

band

the active band when this frame was received

freq

frequency the radio was tuned to when receiving this frame, in MHz

signal

signal strength when receiving this frame, either in dBm, in dB or unspecified depending on the hardware capabilities flags `IEEE80211_HW_SIGNAL_*`

noise

noise when receiving this frame, in dBm.

qual

overall signal quality indication, in percent (0-100).

antenna

antenna used

rate\_idx

index of data rate into band's supported rates

flag

`RX_FLAG_*`

## Description

The low-level driver should provide this information (the subset supported by hardware) to the 802.11 code with each received frame.

## enum mac80211\_rx\_flags

**LINUX**

## Name

enum mac80211\_rx\_flags — receive flags

## Synopsis

```
enum mac80211_rx_flags {
    RX_FLAG_MMIC_ERROR,
    RX_FLAG_DECRYPTED,
    RX_FLAG_RADIOTAP,
    RX_FLAG_MMIC_STRIPPED,
    RX_FLAG_IV_STRIPPED,
    RX_FLAG_FAILED_FCS_CRC,
    RX_FLAG_FAILED_PLCP_CRC,
    RX_FLAG_TSFT
};
```

## Constants

**RX\_FLAG\_MMIC\_ERROR**

Michael MIC error was reported on this frame. Use together with  
RX\_FLAG\_MMIC\_STRIPPED.

**RX\_FLAG\_DECRYPTED**

This frame was decrypted in hardware.

**RX\_FLAG\_RADIOTAP**

This frame starts with a radiotap header.

**RX\_FLAG\_MMIC\_STRIPPED**

the Michael MIC is stripped off this frame, verification has been done by the  
hardware.

**RX\_FLAG\_IV\_STRIPPED**

The IV/ICV are stripped from this frame. If this flag is set, the stack cannot do  
any replay detection hence the driver or hardware will have to do that.



`RX_FLAG_FAILED_FCS_CRC`

Set this flag if the FCS check failed on the frame.

`RX_FLAG_FAILED_PLCP_CRC`

Set this flag if the PCLP check failed on the frame.

`RX_FLAG_TSFT`

The timestamp passed in the RX status (*mtime* field) is valid. This is useful in monitor mode and necessary for beacon frames to enable IBSS merging.

## Description

These flags are used with the *flag* member of struct `ieee80211_rx_status`.

**/usr/src/packages/BUILD/linux-2.6.27.19-5//include/net/mac80211.h**

## Name

`/usr/src/packages/BUILD/linux-2.6.27.19-5//include/net/mac80211.h`  
— Document generation inconsistency

## Oops

### Warning

The template for this document tried to insert the structured comment from the file

`/usr/src/packages/BUILD/linux-2.6.27.19-5//include/net/mac80211.h`  
at this point, but none was found. This dummy section is inserted to allow generation to continue.

## **/usr/src/packages/BUILD/linux-2.6.27.19-5//include/net/mac80211.h**

### **Name**

`/usr/src/packages/BUILD/linux-2.6.27.19-5//include/net/mac80211.h`  
— Document generation inconsistency

### **Oops**

#### **Warning**

The template for this document tried to insert the structured comment from the file

`/usr/src/packages/BUILD/linux-2.6.27.19-5//include/net/mac80211.h`  
at this point, but none was found. This dummy section is inserted to allow generation to continue.

## **ieee80211\_rx**

### **LINUX**

Kernel Hackers Manual February 2009

### **Name**

`ieee80211_rx` — receive frame

## Synopsis

```
void ieee80211_rx (struct ieee80211_hw * hw, struct sk_buff *  
skb, struct ieee80211_rx_status * status);
```

## Arguments

*hw*

the hardware this frame came in on

*skb*

the buffer to receive, owned by mac80211 after this call

*status*

status of this frame; the status pointer need not be valid after this function returns

## Description

Use this function to hand received frames to mac80211. The receive buffer in *skb* must start with an IEEE 802.11 header or a radiotap header if `RX_FLAG_RADIOTAP` is set in the *status* flags.

This function may not be called in IRQ context. Calls to this function for a single hardware must be synchronized against each other. Calls to this function and `ieee80211_rx_irqsafe` may not be mixed for a single hardware.

## ieee80211\_rx\_irqsafe

**LINUX**

## Name

`ieee80211_rx_irqsafe` — receive frame

## Synopsis

```
void ieee80211_rx_irqsafe (struct ieee80211_hw * hw, struct  
sk_buff * skb, struct ieee80211_rx_status * status);
```

## Arguments

*hw*

the hardware this frame came in on

*skb*

the buffer to receive, owned by mac80211 after this call

*status*

status of this frame; the status pointer need not be valid after this function returns and is not freed by mac80211, it is recommended that it points to a stack area

## Description

Like `ieee80211_rx` but can be called in IRQ context (internally defers to a tasklet.)

Calls to this function and `ieee80211_rx` may not be mixed for a single hardware.

# ieee80211\_tx\_status

## LINUX

Kernel Hackers Manual February 2009

### Name

ieee80211\_tx\_status — transmit status callback

### Synopsis

```
void ieee80211_tx_status (struct ieee80211_hw * hw, struct  
sk_buff * skb);
```

### Arguments

*hw*

the hardware the frame was transmitted by

*skb*

the frame that was transmitted, owned by mac80211 after this call

### Description

Call this function for all transmitted frames after they have been transmitted. It is permissible to not call this function for multicast frames but this can affect statistics.

This function may not be called in IRQ context. Calls to this function for a single hardware must be synchronized against each other. Calls to this function and `ieee80211_tx_status_irqsafe` may not be mixed for a single hardware.

# ieee80211\_tx\_status\_irqsafe

## LINUX

Kernel Hackers Manual February 2009

### Name

`ieee80211_tx_status_irqsafe` — IRQ-safe transmit status callback

### Synopsis

```
void ieee80211_tx_status_irqsafe (struct ieee80211_hw * hw,  
struct sk_buff * skb);
```

### Arguments

*hw*

the hardware the frame was transmitted by

*skb*

the frame that was transmitted, owned by mac80211 after this call

### Description

Like `ieee80211_tx_status` but can be called in IRQ context (internally defers to a tasklet.)

Calls to this function and `ieee80211_tx_status` may not be mixed for a single hardware.

# ieee80211\_rts\_get

## LINUX

Kernel Hackers Manual February 2009

### Name

ieee80211\_rts\_get — RTS frame generation function

### Synopsis

```
void ieee80211_rts_get (struct ieee80211_hw * hw, struct
ieee80211_vif * vif, const void * frame, size_t frame_len,
const struct ieee80211_tx_info * frame_txctl, struct
ieee80211_rts * rts);
```

### Arguments

*hw*

pointer obtained from `ieee80211_alloc_hw`.

*vif*

struct `ieee80211_vif` pointer from struct `ieee80211_if_init_conf`.

*frame*

pointer to the frame that is going to be protected by the RTS.

*frame\_len*

the frame length (in octets).

*frame\_txctl*

struct `ieee80211_tx_info` of the frame.

*rts*

The buffer where to store the RTS frame.

## Description

If the RTS frames are generated by the host system (i.e., not in hardware/firmware), the low-level driver uses this function to receive the next RTS frame from the 802.11 code. The low-level is responsible for calling this function before and RTS frame is needed.

## ieee80211\_rts\_duration

### LINUX

Kernel Hackers Manual February 2009

### Name

`ieee80211_rts_duration` — Get the duration field for an RTS frame

### Synopsis

```
__le16 ieee80211_rts_duration (struct ieee80211_hw * hw,  
struct ieee80211_vif * vif, size_t frame_len, const struct  
ieee80211_tx_info * frame_txctl);
```

### Arguments

*hw*

pointer obtained from `ieee80211_alloc_hw`.

*vif*

struct `ieee80211_vif` pointer from struct `ieee80211_if_init_conf`.

*frame\_len*

the length of the frame that is going to be protected by the RTS.



*frame\_txctl*

struct ieee80211\_tx\_info of the frame.

## Description

If the RTS is generated in firmware, but the host system must provide the duration field, the low-level driver uses this function to receive the duration field value in little-endian byteorder.

# ieee80211\_ctstoself\_get

## LINUX

Kernel Hackers Manual February 2009

## Name

ieee80211\_ctstoself\_get — CTS-to-self frame generation function

## Synopsis

```
void ieee80211_ctstoself_get (struct ieee80211_hw * hw, struct
ieee80211_vif * vif, const void * frame, size_t frame_len,
const struct ieee80211_tx_info * frame_txctl, struct
ieee80211_cts * cts);
```

## Arguments

*hw*

pointer obtained from `ieee80211_alloc_hw`.

*vif*

struct ieee80211\_vif pointer from struct ieee80211\_if\_init\_conf.

*frame*

pointer to the frame that is going to be protected by the CTS-to-self.

*frame\_len*

the frame length (in octets).

*frame\_txctl*

struct ieee80211\_tx\_info of the frame.

*cts*

The buffer where to store the CTS-to-self frame.

## Description

If the CTS-to-self frames are generated by the host system (i.e., not in hardware/firmware), the low-level driver uses this function to receive the next CTS-to-self frame from the 802.11 code. The low-level is responsible for calling this function before and CTS-to-self frame is needed.

# ieee80211\_ctstoself\_duration

## LINUX

Kernel Hackers Manual February 2009

## Name

`ieee80211_ctstoself_duration` — Get the duration field for a CTS-to-self frame

## Synopsis

```
__le16 ieee80211_ctstoself_duration (struct ieee80211_hw * hw,  
struct ieee80211_vif * vif, size_t frame_len, const struct  
ieee80211_tx_info * frame_txctl);
```

## Arguments

*hw*

pointer obtained from `ieee80211_alloc_hw`.

*vif*

struct `ieee80211_vif` pointer from struct `ieee80211_if_init_conf`.

*frame\_len*

the length of the frame that is going to be protected by the CTS-to-self.

*frame\_txctl*

struct `ieee80211_tx_info` of the frame.

## Description

If the CTS-to-self is generated in firmware, but the host system must provide the duration field, the low-level driver uses this function to receive the duration field value in little-endian byteorder.

## ieee80211\_generic\_frame\_duration

**LINUX**

## Name

`ieee80211_generic_frame_duration` — Calculate the duration field for a frame

## Synopsis

```
__le16 ieee80211_generic_frame_duration (struct ieee80211_hw *  
hw, struct ieee80211_vif * vif, size_t frame_len, struct  
ieee80211_rate * rate);
```

## Arguments

*hw*

pointer obtained from `ieee80211_alloc_hw`.

*vif*

struct `ieee80211_vif` pointer from struct `ieee80211_if_init_conf`.

*frame\_len*

the length of the frame.

*rate*

the rate at which the frame is going to be transmitted.

## Description

Calculate the duration field of some generic frame, given its length and transmission rate (in 100kbps).

# ieee80211\_get\_hdrlen\_from\_skb

## LINUX

Kernel Hackers Manual February 2009

### Name

`ieee80211_get_hdrlen_from_skb` — get header length from data

### Synopsis

```
unsigned int ieee80211_get_hdrlen_from_skb (const struct  
sk_buff * skb);
```

### Arguments

*skb*

the frame

### Description

Given an `skb` with a raw 802.11 header at the data pointer this function returns the 802.11 header length in bytes (not including encryption headers). If the data in the `sk_buff` is too short to contain a valid 802.11 header the function returns 0.

# ieee80211\_get\_hdrlen

## LINUX

## Name

`ieee80211_get_hdrlen` — get header length from frame control

## Synopsis

```
int ieee80211_get_hdrlen (u16 fc);
```

## Arguments

*fc*

the frame control field (in CPU endianness)

## Description

This function returns the 802.11 header length in bytes (not including encryption headers.)

# ieee80211\_wake\_queue

## LINUX

## Name

`ieee80211_wake_queue` — wake specific queue

## Synopsis

```
void ieee80211_wake_queue (struct ieee80211_hw * hw, int  
queue);
```

## Arguments

*hw*

pointer as obtained from `ieee80211_alloc_hw`.

*queue*

queue number (counted from zero).

## Description

Drivers should use this function instead of `netif_wake_queue`.

# ieee80211\_stop\_queue

## LINUX

Kernel Hackers Manual February 2009

## Name

`ieee80211_stop_queue` — stop specific queue

## Synopsis

```
void ieee80211_stop_queue (struct ieee80211_hw * hw, int  
queue);
```

## Arguments

*hw*

pointer as obtained from `ieee80211_alloc_hw`.

*queue*

queue number (counted from zero).

## Description

Drivers should use this function instead of `netif_stop_queue`.

**/usr/src/packages/BUILD/linux-2.6.27.19-5//include/net/mac80211.h**

## Name

`/usr/src/packages/BUILD/linux-2.6.27.19-5//include/net/mac80211.h`  
— Document generation inconsistency

## Oops

### Warning

The template for this document tried to insert the structured comment from the file

`/usr/src/packages/BUILD/linux-2.6.27.19-5//include/net/mac80211.h`  
at this point, but none was found. This dummy section is inserted to allow generation to continue.



# ieee80211\_stop\_queues

## LINUX

Kernel Hackers Manual February 2009

### Name

`ieee80211_stop_queues` — stop all queues

### Synopsis

```
void ieee80211_stop_queues (struct ieee80211_hw * hw);
```

### Arguments

*hw*

pointer as obtained from `ieee80211_alloc_hw`.

### Description

Drivers should use this function instead of `netif_stop_queue`.

# ieee80211\_wake\_queues

## LINUX

## Name

`ieee80211_wake_queues` — wake all queues

## Synopsis

```
void ieee80211_wake_queues (struct ieee80211_hw * hw);
```

## Arguments

*hw*

pointer as obtained from `ieee80211_alloc_hw`.

## Description

Drivers should use this function instead of `netif_wake_queue`.

# Chapter 5. Frame filtering

mac80211 requires to see many management frames for proper operation, and users may want to see many more frames when in monitor mode. However, for best CPU usage and power consumption, having as few frames as possible percolate through the stack is desirable. Hence, the hardware should filter as much as possible.

To achieve this, mac80211 uses filter flags (see below) to tell the driver's `configure_filter` function which frames should be passed to mac80211 and which should be filtered out.

The `configure_filter` callback is invoked with the parameters `mc_count` and `mc_list` for the combined multicast address list of all virtual interfaces, `changed_flags` telling which flags were changed and `total_flags` with the new flag states.

If your device has no multicast address filters your driver will need to check both the `FIF_ALLMULTI` flag and the `mc_count` parameter to see whether multicast frames should be accepted or dropped.

All unsupported flags in `total_flags` must be cleared. Hardware does not support a flag if it is incapable of `_passing_` the frame to the stack. Otherwise the driver must ignore the flag, but not clear it. You must `_only_` clear the flag (announce no support for the flag to mac80211) if you are not able to pass the packet type to the stack (so the hardware always filters it). So for example, you should clear `FIF_CONTROL`, if your hardware always filters control frames. If your hardware always passes control frames to the kernel and is incapable of filtering them, you do `_not_` clear the `FIF_CONTROL` flag. This rule applies to all other FIF flags as well.

## enum ieee80211\_filter\_flags

### LINUX

Kernel Hackers Manual February 2009

### Name

enum ieee80211\_filter\_flags — hardware filter flags

### Synopsis

```
enum ieee80211_filter_flags {
```

```
FIF_PROMISC_IN_BSS,  
FIF_ALLMULTI,  
FIF_FCSFAIL,  
FIF_PLCPFAIL,  
FIF_BCN_PRBRESP_PROMISC,  
FIF_CONTROL,  
FIF_OTHER_BSS  
};
```

## Constants

### FIF\_PROMISC\_IN\_BSS

promiscuous mode within your BSS, think of the BSS as your network segment and then this corresponds to the regular ethernet device promiscuous mode.

### FIF\_ALLMULTI

pass all multicast frames, this is used if requested by the user or if the hardware is not capable of filtering by multicast address.

### FIF\_FCSFAIL

pass frames with failed FCS (but you need to set the RX\_FLAG\_FAILED\_FCS\_CRC for them)

### FIF\_PLCPFAIL

pass frames with failed PLCP CRC (but you need to set the RX\_FLAG\_FAILED\_PLCP\_CRC for them)

### FIF\_BCN\_PRBRESP\_PROMISC

This flag is set during scanning to indicate to the hardware that it should not filter beacons or probe responses by BSSID. Filtering them can greatly reduce the amount of processing mac80211 needs to do and the amount of CPU wakeups, so you should honour this flag if possible.

### FIF\_CONTROL

pass control frames, if PROMISC\_IN\_BSS is not set then only those addressed to this station

### FIF\_OTHER\_BSS

pass frames destined to other BSSes

## **Frame filtering**

These flags determine what the filter in hardware should be programmed to let through and what should not be passed to the stack. It is always safe to pass more frames than requested, but this has negative impact on power consumption.



# II. Advanced driver interface

## Table of Contents

<b>6. Hardware crypto acceleration .....</b>	<b>57</b>
<b>7. Multiple queues and QoS support .....</b>	<b>63</b>
<b>8. Access point mode support.....</b>	<b>67</b>
<b>9. Supporting multiple virtual interfaces.....</b>	<b>71</b>
<b>10. Hardware scan offload.....</b>	<b>73</b>

Information contained within this part of the book is of interest only for advanced interaction of mac80211 with drivers to exploit more hardware capabilities and improve performance.





# Chapter 6. Hardware crypto acceleration

mac80211 is capable of taking advantage of many hardware acceleration designs for encryption and decryption operations.

The `set_key` callback in the struct `ieee80211_ops` for a given device is called to enable hardware acceleration of encryption and decryption. The callback takes an *address* parameter that will be the broadcast address for default keys, the other station's hardware address for individual keys or the zero address for keys that will be used only for transmission. Multiple transmission keys with the same key index may be used when VLANs are configured for an access point.

The *local\_address* parameter will always be set to our own address, this is only relevant if you support multiple local addresses.

When transmitting, the TX control data will use the *hw\_key\_idx* selected by the driver by modifying the struct `ieee80211_key_conf` pointed to by the *key* parameter to the `set_key` function.

The `set_key` call for the `SET_KEY` command should return 0 if the key is now in use, `-EOPNOTSUPP` or `-ENOSPC` if it couldn't be added; if you return 0 then *hw\_key\_idx* must be assigned to the hardware key index, you are free to use the full u8 range.

When the cmd is `DISABLE_KEY` then it must succeed.

Note that it is permissible to not decrypt a frame even if a key for it has been uploaded to hardware, the stack will not make any decision based on whether a key has been uploaded or not but rather based on the receive flags.

The struct `ieee80211_key_conf` structure pointed to by the *key* parameter is guaranteed to be valid until another call to `set_key` removes it, but it can only be used as a cookie to differentiate keys.

In TKIP some HW need to be provided a phase 1 key, for RX decryption acceleration (i.e. iwlwifi). Those drivers should provide `update_tkip_key` handler. The `update_tkip_key` call updates the driver with the new phase 1 key. This happens everytime the iv16 wraps around (every 65536 packets). The `set_key` call will happen only once for each key (unless the AP did rekeying), it will not include a valid phase 1 key. The valid phase 1 key is provided by `update_tkip_key` only. The trigger that makes mac80211 call this handler is software decryption with wrap around of iv16.

## enum set\_key\_cmd

### LINUX

Kernel Hackers Manual February 2009

### Name

enum set\_key\_cmd — key command

### Synopsis

```
enum set_key_cmd {  
    SET_KEY,  
    DISABLE_KEY  
};
```

### Constants

SET\_KEY

a key is set

DISABLE\_KEY

a key must be disabled

### Description

Used with the `set_key` callback in struct `ieee80211_ops`, this indicates whether a key is being removed or added.

## struct ieee80211\_key\_conf

### LINUX

## Name

`struct ieee80211_key_conf` — key information

## Synopsis

```

struct ieee80211_key_conf {
    enum ieee80211_key_alg alg;
    u8 hw_key_idx;
    u8 flags;
    s8 keyidx;
    u8 keylen;
    u8 key[0];
};

```

## Members

`alg`

The key algorithm.

`hw_key_idx`

To be set by the driver, this is the key index the driver wants to be given when a frame is transmitted and needs to be encrypted in hardware.

`flags`

key flags, see enum `ieee80211_key_flags`.

`keyidx`

the key index (0-3)

`keylen`

key material length

`key[0]`

key material. For `ALG_TKIP` the key is encoded as a 256-bit (32 byte)

## Description

This key information is given by mac80211 to the driver by the `set_key` callback in struct `ieee80211_ops`.

## data block

- Temporal Encryption Key (128 bits) - Temporal Authenticator Tx MIC Key (64 bits) - Temporal Authenticator Rx MIC Key (64 bits)

## enum ieee80211\_key\_alg

### LINUX

Kernel Hackers Manual February 2009

## Name

`enum ieee80211_key_alg` — key algorithm

## Synopsis

```
enum ieee80211_key_alg {  
    ALG_WEP,  
    ALG_TKIP,  
    ALG_CCMP  
};
```

## Constants

`ALG_WEP`

WEP40 or WEP104

`ALG_TKIP`

TKIP

ALG\_CCMP

CCMP (AES)

## enum ieee80211\_key\_flags

### LINUX

Kernel Hackers Manual February 2009

### Name

enum ieee80211\_key\_flags — key flags

### Synopsis

```
enum ieee80211_key_flags {
    IEEE80211_KEY_FLAG_WMM_STA,
    IEEE80211_KEY_FLAG_GENERATE_IV,
    IEEE80211_KEY_FLAG_GENERATE_MMIC,
    IEEE80211_KEY_FLAG_PAIRWISE
};
```

### Constants

IEEE80211\_KEY\_FLAG\_WMM\_STA

Set by mac80211, this flag indicates that the STA this key will be used with could be using QoS.

IEEE80211\_KEY\_FLAG\_GENERATE\_IV

This flag should be set by the driver to indicate that it requires IV generation for this particular key.

IEEE80211\_KEY\_FLAG\_GENERATE\_MMIC

This flag should be set by the driver for a TKIP key if it requires Michael MIC generation in software.

## IEEE80211\_KEY\_FLAG\_PAIRWISE

Set by mac80211, this flag indicates that the key is pairwise rather than a shared key.

## Description

These flags are used for communication about keys between the driver and mac80211, with the *flags* parameter of struct `ieee80211_key_conf`.

# Chapter 7. Multiple queues and QoS support

TBD

## struct ieee80211\_tx\_queue\_params

**LINUX**

Kernel Hackers Manual February 2009

### Name

struct ieee80211\_tx\_queue\_params — transmit queue configuration

### Synopsis

```
struct ieee80211_tx_queue_params {
    u16 txop;
    u16 cw_min;
    u16 cw_max;
    u8 aifs;
};
```

### Members

txop

maximum burst time in units of 32 usecs, 0 meaning disabled

cw\_min

minimum contention window [a value of the form  $2^n - 1$  in the range 1..32767]

cw\_max

maximum contention window [like *cw\_min*]

aifs

arbitration interface space [0..255]

## Description

The information provided in this structure is required for QoS transmit queue configuration. Cf. IEEE 802.11 7.3.2.29.

**/usr/src/packages/BUILD/linux-2.6.27.19-5//include/net/mac80211.h**

## Name

/usr/src/packages/BUILD/linux-2.6.27.19-5//include/net/mac80211.h  
— Document generation inconsistency

## Oops

### Warning

The template for this document tried to insert the structured comment from the file

/usr/src/packages/BUILD/linux-2.6.27.19-5//include/net/mac80211.h  
at this point, but none was found. This dummy section is inserted to allow generation to continue.

**/usr/src/packages/BUILD/linux-2.6.27.19-5//include/net/mac80211.h**



## Name

`/usr/src/packages/BUILD/linux-2.6.27.19-5//include/net/mac80211.h`  
— Document generation inconsistency

## Oops

### Warning

The template for this document tried to insert the structured comment from the file

`/usr/src/packages/BUILD/linux-2.6.27.19-5//include/net/mac80211.h`  
at this point, but none was found. This dummy section is inserted to allow generation to continue.



# Chapter 8. Access point mode support

TBD

Some parts of the `if_conf` should be discussed here instead

Insert notes about VLAN interfaces with hw crypto here or in the hw crypto chapter.

## ieee80211\_get\_buffered\_bc

### LINUX

Kernel Hackers Manual February 2009

### Name

`ieee80211_get_buffered_bc` — accessing buffered broadcast and multicast frames

### Synopsis

```
struct sk_buff * ieee80211_get_buffered_bc (struct
ieee80211_hw * hw, struct ieee80211_vif * vif);
```

### Arguments

*hw*

pointer as obtained from `ieee80211_alloc_hw`.

*vif*

struct `ieee80211_vif` pointer from struct `ieee80211_if_init_conf`.

## Description

Function for accessing buffered broadcast and multicast frames. If hardware/firmware does not implement buffering of broadcast/multicast frames when power saving is used, 802.11 code buffers them in the host memory. The low-level driver uses this function to fetch next buffered frame. In most cases, this is used when generating beacon frame. This function returns a pointer to the next buffered skb or NULL if no more buffered frames are available.

## Note

buffered frames are returned only after DTIM beacon frame was generated with `ieee80211_beacon_get` and the low-level driver must thus call `ieee80211_beacon_get` first. `ieee80211_get_buffered_bc` returns NULL if the previous generated beacon was not DTIM, so the low-level driver does not need to check for DTIM beacons separately and should be able to use common code for all beacons.

# ieee80211\_beacon\_get

## LINUX

Kernel Hackers Manual February 2009

## Name

`ieee80211_beacon_get` — beacon generation function

## Synopsis

```
struct sk_buff * ieee80211_beacon_get (struct ieee80211_hw *  
hw, struct ieee80211_vif * vif);
```

## Arguments

*hw*

pointer obtained from `ieee80211_alloc_hw`.

*vif*

struct `ieee80211_vif` pointer from struct `ieee80211_if_init_conf`.

## Description

If the beacon frames are generated by the host system (i.e., not in hardware/firmware), the low-level driver uses this function to receive the next beacon frame from the 802.11 code. The low-level is responsible for calling this function before beacon data is needed (e.g., based on hardware interrupt). Returned `skb` is used only once and low-level driver is responsible of freeing it.



# Chapter 9. Supporting multiple virtual interfaces

TBD

Note: WDS with identical MAC address should almost always be OK

Insert notes about having multiple virtual interfaces with different MAC addresses here, note which configurations are supported by mac80211, add notes about supporting hw crypto with it.





# Chapter 10. Hardware scan offload

TBD

## ieee80211\_scan\_completed

### LINUX

Kernel Hackers Manual February 2009

### Name

`ieee80211_scan_completed` — completed hardware scan

### Synopsis

```
void ieee80211_scan_completed (struct ieee80211_hw * hw);
```

### Arguments

*hw*

the hardware that finished the scan

### Description

When hardware scan offload is used (i.e. the `hw_scan` callback is assigned) this function needs to be called by the driver to notify `mac80211` that the scan finished.



# III. Rate control interface

## Table of Contents

11. dummy chapter .....	77
-------------------------	----

TBD

This part of the book describes the rate control algorithm interface and how it relates to mac80211 and drivers.



# Chapter 11. dummy chapter

TBD



# IV. Internals

## Table of Contents

<b>12. Key handling.....</b>	<b>81</b>
<b>13. Receive processing.....</b>	<b>83</b>
<b>14. Transmit processing .....</b>	<b>85</b>
<b>15. Station info handling.....</b>	<b>87</b>
<b>16. Synchronisation.....</b>	<b>97</b>

TBD

This part of the book describes mac80211 internals.





# Chapter 12. Key handling

## 12.1. Key handling basics

Key handling in mac80211 is done based on per-interface (`sub_if_data`) keys and per-station keys. Since each station belongs to an interface, each station key also belongs to that interface.

Hardware acceleration is done on a best-effort basis, for each key that is eligible the hardware is asked to enable that key but if it cannot do that the key is simply kept for software encryption. There is currently no way of knowing this except by looking into debugfs.

All key operations are protected internally so you can call them at any time.

Within mac80211, key references are, just as STA structure references, protected by RCU. Note, however, that some things are unprotected, namely the `key->sta` dereferences within the hardware acceleration functions. This means that `sta_info_destroy` must flush the key todo list.

All the direct key list manipulation functions must not sleep because they can operate on STA info structs that are protected by RCU.

## 12.2. MORE TBD

TBD



# Chapter 13. Receive processing

TBD



# Chapter 14. Transmit processing

TBD



# Chapter 15. Station info handling

## 15.1. Programming information

### struct sta\_info

#### LINUX

Kernel Hackers Manual February 2009

#### Name

struct sta\_info — STA information

#### Synopsis

```
struct sta_info {
    struct list_head list;
    struct sta_info * hnext;
    struct ieee80211_local * local;
    struct ieee80211_sub_if_data * sdata;
    struct ieee80211_key * key;
    struct rate_control_ref * rate_ctrl;
    void * rate_ctrl_priv;
    spinlock_t lock;
    spinlock_t flaglock;
    struct ieee80211_ht_info ht_info;
    u64 supp_rates[IEEE80211_NUM_BANDS];
    u8 addr[ETH_ALEN];
    u16 aid;
    u16 listen_interval;
    u8 pin_status;
    u32 flags;
    struct sk_buff_head ps_tx_buf;
    struct sk_buff_head tx_filtered;
    unsigned long rx_packets;
    unsigned long rx_bytes;
    unsigned long wep_weak_iv_count;
    unsigned long last_rx;
    unsigned long num_duplicates;
```

## Chapter 15. Station info handling

```
    unsigned long rx_fragments;
    unsigned long rx_dropped;
    int last_signal;
    int last_qual;
    int last_noise;
    __le16 last_seq_ctrl[NUM_RX_DATA_QUEUES];
#ifdef CONFIG_MAC80211_DEBUG_COUNTERS
    unsigned int wme_rx_queue[NUM_RX_DATA_QUEUES];
#endif
    unsigned long tx_filtered_count;
    unsigned long tx_retry_failed;
    unsigned long tx_retry_count;
    u32 tx_num_consecutive_failures;
    u32 tx_num_mpdu_ok;
    u32 tx_num_mpdu_fail;
    unsigned int fail_avg;
    unsigned long tx_packets;
    unsigned long tx_bytes;
    unsigned long tx_fragments;
    int txrate_idx;
    int last_txrate_idx;
#ifdef CONFIG_MAC80211_DEBUG_COUNTERS
    unsigned int wme_tx_queue[NUM_RX_DATA_QUEUES];
#endif
    struct sta_ampdu_mlme ampdu_mlme;
    u8 timer_to_tid[STA_TID_NUM];
    u8 tid_to_tx_q[STA_TID_NUM];
#ifdef CONFIG_MAC80211_MESH
    __le16 llid;
    __le16 plid;
    __le16 reason;
    u8 plink_retries;
    bool ignore_plink_timer;
    enum plink_state plink_state;
    u32 plink_timeout;
    struct timer_list plink_timer;
#endif
#ifdef CONFIG_MAC80211_DEBUGFS
    struct sta_info_debugfsdentries debugfs;
#endif
};
```



## Members

list

global linked list entry

hnext

hash table linked list pointer

local

pointer to the global information

sdata

TBD

key

TBD

rate\_ctrl

TBD

rate\_ctrl\_priv

TBD

lock

used for locking all fields that require locking, see comments in the header file.

flaglock

spinlock for flags accesses

ht\_info

HT capabilities of this STA

supp\_rates[IEEE80211\_NUM\_BANDS]

Bitmap of supported rates (per band)

addr[ETH\_ALEN]

MAC address of this STA

aid

STA's unique AID (1..2007, 0 = not assigned yet), only used in AP (and IBSS?) mode

listen\_interval

TBD

pin\_status

TBD

flags

STA flags, see enum `ieee80211_sta_info_flags`

ps\_tx\_buf

buffer of frames to transmit to this station when it leaves power saving state

tx\_filtered

buffer of frames we already tried to transmit but were filtered by hardware due to STA having entered power saving state

rx\_packets

Number of MSDUs received from this STA

rx\_bytes

Number of bytes received from this STA

wep\_weak\_iv\_count

TBD

last\_rx

TBD

num\_duplicates

number of duplicate frames received from this STA

rx\_fragments

number of received MPDUs

rx\_dropped

number of dropped MPDUs from this STA

last\_signal

signal of last received frame from this STA

last\_qual

qual of last received frame from this STA

last\_noise

noise of last received frame from this STA

last\_seq\_ctrl[NUM\_RX\_DATA\_QUEUES]

last received seq/frag number from this STA (per RX queue)

wme\_rx\_queue[NUM\_RX\_DATA\_QUEUES]

TBD

tx\_filtered\_count

TBD

tx\_retry\_failed

TBD

tx\_retry\_count

TBD

tx\_num\_consecutive\_failures

TBD

tx\_num\_mpdu\_ok

TBD

tx\_num\_mpdu\_fail

TBD

fail\_avg

moving percentage of failed MSDUs

tx\_packets

number of RX/TX MSDUs

tx\_bytes

TBD

## *Chapter 15. Station info handling*

tx\_fragments  
    number of transmitted MPDUs

txrate\_idx  
    TBD

last\_txrate\_idx  
    TBD

wme\_tx\_queue[NUM\_RX\_DATA\_QUEUES]  
    TBD

ampdu\_mlme  
    TBD

timer\_to\_tid[STA\_TID\_NUM]  
    identity mapping to ID timers

tid\_to\_tx\_q[STA\_TID\_NUM]  
    map tid to tx queue

llid  
    Local link ID

plid  
    Peer link ID

reason  
    Cancel reason on PLINK\_HOLDING state

plink\_retries  
    Retries in establishment

ignore\_plink\_timer  
    TBD

plink\_state  
    TBD

plink\_timeout  
    TBD

plink\_timer

TBD

debugfs

debug filesystem info

## Description

This structure collects information about a station that mac80211 is communicating with.

# enum ieee80211\_sta\_info\_flags

## LINUX

Kernel Hackers Manual February 2009

## Name

enum ieee80211\_sta\_info\_flags — Stations flags

## Synopsis

```
enum ieee80211_sta_info_flags {
    WLAN_STA_AUTH,
    WLAN_STA_ASSOC,
    WLAN_STA_PS,
    WLAN_STA_AUTHORIZED,
    WLAN_STA_SHORT_PREAMBLE,
    WLAN_STA_ASSOC_AP,
    WLAN_STA_WME,
    WLAN_STA_WDS,
    WLAN_STA_PSPOLL,
    WLAN_STA_CLEAR_PS_FILT
};
```

## Constants

WLAN\_STA\_AUTH

Station is authenticated.

WLAN\_STA\_ASSOC

Station is associated.

WLAN\_STA\_PS

Station is in power-save mode

WLAN\_STA\_AUTHORIZED

Station is authorized to send/receive traffic. This bit is always checked so needs to be enabled for all stations when virtual port control is not in use.

WLAN\_STA\_SHORT\_PREAMBLE

Station is capable of receiving short-preamble frames.

WLAN\_STA\_ASSOC\_AP

We're associated to that station, it is an AP.

WLAN\_STA\_WME

Station is a QoS-STA.

WLAN\_STA\_WDS

Station is one of our WDS peers.

WLAN\_STA\_PSPOLL

Station has just PS-polled us.

WLAN\_STA\_CLEAR\_PS\_FILT

Clear PS filter in hardware (using the IEEE80211\_TX\_CTL\_CLEAR\_PS\_FILT control flag) when the next frame to this station is transmitted.

## Description

These flags are used with struct `sta_info`'s `flags` member.

## 15.2. STA information lifetime rules

STA info structures (`struct sta_info`) are managed in a hash table for faster lookup and a list for iteration. They are managed using RCU, i.e. access to the list and hash table is protected by RCU.

Upon allocating a STA info structure with `sta_info_alloc`, the caller owns that structure. It must then either destroy it using `sta_info_destroy` (which is pretty useless) or insert it into the hash table using `sta_info_insert` which demotes the reference from ownership to a regular RCU-protected reference; if the function is called without protection by an RCU critical section the reference is instantly invalidated. Note that the caller may not do much with the STA info before inserting it, in particular, it may not start any mesh peer link management or add encryption keys.

When the insertion fails (`sta_info_insert` returns non-zero), the structure will have been freed by `sta_info_insert`!

Because there are debugfs entries for each station, and adding those must be able to sleep, it is also possible to “pin” a station entry, that means it can be removed from the hash table but not be freed. See the comment in `__sta_info_unlink` for more information, this is an internal capability only.

In order to remove a STA info structure, the caller needs to first unlink it (`sta_info_unlink`) from the list and hash tables and then destroy it; `sta_info_destroy` will wait for an RCU grace period to elapse before actually freeing it. Due to the pinning and the possibility of multiple callers trying to remove the same STA info at the same time, `sta_info_unlink` can clear the STA info pointer it is passed to indicate that the STA info is owned by somebody else now.

If `sta_info_unlink` did not clear the pointer then the caller owns the STA info structure now and is responsible of destroying it with a call to `sta_info_destroy`.

In all other cases, there is no concept of ownership on a STA entry, each structure is owned by the global hash table/list until it is removed. All users of the structure need to be RCU protected so that the structure won't be freed before they are done using it.





# Chapter 16. Synchronisation

TBD

Locking, lots of RCU

